

HEXADECIIMAL AND DECIMAL CONVERSION

HEXADECIIMAL COLUMNS											
6		5		4		3		2		1	
HEX	DEC	HEX	DEC	HEX	DEC	HEX	DEC	HEX	DEC	HEX	DEC
0	0	0	0	0	0	0	0	0	0	0	0
1	1,048,576	1	65,536	1	4,096	1	256	1	16	1	1
2	2,097,152	2	131,072	2	8,192	2	512	2	32	2	2
3	3,145,728	3	196,608	3	12,288	3	768	3	48	3	3
4	4,194,304	4	262,144	4	16,384	4	1,024	4	64	4	4
5	5,242,880	5	327,680	5	20,480	5	1,280	5	80	5	5
6	6,291,456	6	393,216	6	24,576	6	1,536	6	96	6	6
7	7,340,032	7	458,752	7	28,672	7	1,792	7	112	7	7
8	8,388,608	8	524,288	8	32,768	8	2,048	8	128	8	8
9	9,437,184	9	589,824	9	36,864	9	2,304	9	144	9	9
A	10,485,760	A	655,360	A	40,960	A	2,560	A	160	A	10
B	11,534,336	B	720,896	B	45,056	B	2,816	B	176	B	11
C	12,582,912	C	786,432	C	49,152	C	3,072	C	192	C	12
D	13,631,488	D	851,968	D	53,248	D	3,328	D	208	D	13
E	14,680,064	E	917,504	E	57,344	E	3,584	E	224	E	14
F	15,728,640	F	983,040	F	61,440	F	3,840	F	240	F	15
7654		3210		7654		3210		7654		3210	
Byte		Byte		Byte		Byte		Byte		Byte	

POWERS OF 2

2 ⁿ	n
256	8
512	9
1,024	10
2,048	11
4,096	12
8,192	13
16,384	14
32,768	15
65,536	16
131,072	17
262,144	18
524,288	19
1,048,576	20
2,097,152	21
4,194,304	22
8,388,608	23
16,777,216	24

POWERS OF 16


16 ⁿ	n
1	0
16	1
256	2
4,096	3
65,536	4
1,048,576	5
16,777,216	6
268,435,456	7
4,294,967,296	8
68,719,476,736	9
1,099,511,627,776	10
17,592,186,044,416	11
281,474,976,710,656	12
4,503,599,627,370,496	13
72,057,594,037,927,936	14
1,152,921,504,606,846,976	15

ASCII CHARACTER SET (7-BIT CODE)

LSD	MSD	0	1	2	3	4	5	6	7
		000	001	010	011	100	101	110	111
0	0000	NUL	DLE	SP	0	@	P	q	p
1	0001	SOH	DC1	!	1	A	Q	a	q
2	0010	STX	DC2	"	2	B	R	b	r
3	0011	ETX	DC3	#	3	C	S	c	s
4	0100	EOT	DC4	\$	4	D	T	d	t
5	0101	ENQ	NAK	%	5	E	U	e	u
6	0110	ACK	SYN	&	6	F	V	f	v
7	0111	BEL	ETB	'	7	G	W	g	w
8	1000	BS	CAN	(8	H	X	h	x
9	1001	HT	EM)	9	I	Y	i	y
A	1010	LF	SUB	*	:	J	Z	j	z
B	1011	VT	ESC	+	;	K	[k	{
C	1100	FF	FS	,	<	L	\	l	
D	1101	CR	GS	-	=	M]	m	}
E	1110	SO	RS	.	>	N	^	n	~
F	1111	SI	VS	/	?	O	_	o	DEL

- NUL — Null
- SOH — Start of Heading
- STX — Start of Text
- ETX — End of Text
- EOT — End of Transmission
- ENQ — Enquiry
- ACK — Acknowledge
- BEL — Bell
- BS — Backspace
- HT — Horizontal Tabulation
- LF — Line Feed
- VT — Vertical Tabulation
- FF — Form Feed
- CR — Carriage Return
- SO — Shift Out
- SI — Shift In
- DLE — Data Link Escape
- DC — Device Control
- NAK — Negative Acknowledge
- SYN — Synchronous Idle
- ETB — End of Transmission Block
- CAN — Cancel
- EM — End of Medium
- SUB — Substitute
- ESC — Escape
- FS — File Separator
- GS — Group Separator
- RS — Record Separator
- US — Unit Separator
- SP — Space (Blank)
- DEL — Delete

PUNCHED TAPE FORMAT (ASCII)



OBJECT CODE RECORD FORMAT (ASCII)

Data Record: ;N₁N₀A₂A₁A₀D₁D₀D₃D₂D₁D₀... D₁D₀X₂X₁X₀CR LF
 Last Record: ;00C₂C₁C₀X₂X₁X₀X₀
 where:

- Two hex digits (MSD & LSD) = 1 ASCII character
- ; = Start of record (ASCII '3B')
- N₁N₀ = No. of data bytes in record (hex.) 18₁₀ max.
- = 00 for last record
- A₂A₁A₀ = Starting address (hex)
- D₁D₀ = Two hexadecimal digits = One 8-bit data byte
- X₂X₁X₀ = Record checksum (hex.) Hex sum of all characters in the record except ; and checksum, truncated to 16 bits (four hex digits)
- C₂C₁C₀ = Total number of records (hex)
- CR = Carriage Return (ASCII '0D')
- LF = Line Feed (ASCII '0A')

BACKWARD RELATIVE BRANCH TABLE

LSD	MSD	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F
8	8	128	127	126	125	124	123	122	121	120	119	118	117	116	115	114	113
8	9	112	111	110	109	108	107	106	105	104	103	102	101	100	99	98	97
A	8	96	95	94	93	92	91	90	89	88	87	86	85	84	83	82	81
B	8	80	79	78	77	76	75	74	73	72	71	70	69	68	67	66	65
C	8	64	63	62	61	60	59	58	57	56	55	54	53	52	51	50	49
D	8	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33
E	8	32	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17
F	8	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1

FORWARD RELATIVE BRANCH TABLE

LSD	MSD	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F
0	0	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
1	1	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31
2	2	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47
3	3	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63
4	4	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79
5	5	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95
6	6	96	97	98	99	100	101	102	103	104	105	106	107	108	109	110	111
7	7	112	113	114	115	116	117	118	119	120	121	122	123	124	125	126	127